

# VERIFIKATOR QR KARATA I RFID KARTICA

**KATEGORIJA:** OPREMA ZA TIKETING SISTEME (made in Serbia)

**PART NO:** BCV-1 (QRS-86MF - RFID Čitač 13.56MHz)

**PART NO:** BCV-2 (QRS-86MF - RFID Čitač 125KHz)



## QRS86-MF

QR BARCODE SKENER  
USB; TCP/IP; WG; RS232; RS485



## QRS86-EM

QR BARCODE SKENER  
USB; TCP/IP; WG; RS232; RS485



### U ORIGINALU, NIŽE

QRS-86EM – RFID Čitač 125.00KHz

QRS-86MF - RFID Čitač 13.56MHz

QR Code Access Card Reader is our new intelligent Access Card Reader, Fast reading speed, High recognition rate, Strong compatibility, can connect to any Wiegand input controller, widely used at Office access management, Tourism management, Community visitor access management, Administration Service Hall management, Gates access control, Visitors intelligent machines, Smart home; Upgrade old access control systems etc.

|                  |                                                  |
|------------------|--------------------------------------------------|
| Dimension        | 86L X 86W X42H (mm)                              |
| Material         | PC and Tempered glass                            |
| Interface        | Wiegand26/34, RS485, RS232, USB, TCP/IP optional |
| Decoding support | QR and One dimensional code                      |
| Voltage support  | 4~15V Wide voltage input                         |

|                         |                                                           |
|-------------------------|-----------------------------------------------------------|
| Current                 | 800mA                                                     |
| Reading directions      | Camera centric slant 45°                                  |
| Reading speed           | <200ms                                                    |
| Reading range           | 0~20CM                                                    |
| Reading feature         | Auto-induction, beep hint                                 |
| Light source            | With LED light source itself, Anti-highlight interference |
| Decode mode             | Image decoding                                            |
| Application environment | Temperature: -20°C~70°C                                   |
| Humidity                | 10%~90%                                                   |
| Operate system          | Windows(XP7, 8, 10), Linux                                |
| Indicating status light | Red-Work, Green- Feedback, Light Green-Internet           |
| Reading range           | 3~6CM                                                     |
| Reading card type       | EM or Mifare card                                         |

Restore Factory Settings: Use sharp objects insert into REST hole of QR code reader backside, release till the QR code reader automatically restart.



DC12V



ID/IC card



QR code



-10~60°C



10%~90%



RS485



RS232



WG23/34



USB



TCP/IP

