

- ① CAB. A do RO (A)
SiSi-J: 1 x 3 x 1.50mm²
LiHH: 1 x 2 x 0.50mm² za P1
LiHH: 1 x 2 x 0.50mm² za LED MARK. 1
LiHH: 1 x 3 x 0.50mm² za MINI SEMAFOR (TOWER RGB)
LiHH: 1 x 2 x 0.50mm² za LED RASVETA KABINET
LiHH: 1 x 4 x 0.50mm² za TASTER sa LED indikacijom
LiHH: 1 x 7 x 0.50mm² za RFID Čitač “wiegand”
LiHH: 1 x 3 x 0.75mm² za INTERFON (A), TCS
LiHH: 1 x nn x 0.50mm² za INTERFON (A), PO IZBORU

SiSi-J: 1 x 2 x 1.00mm² za Kiosk Printer 24VDC
LiHH: 1 x 2 x 0.50mm² za Printer “paper end”
LiHH: 1 x 2 x 0.50mm² zaPrinter “paper jam”
LiHH: 1 x 2 x 0.50mm² za Printer “rezerva”
1 x UTP/SFTP za Printer

1 x UTP/SFTP (Rezerva)

- ② RAMPA (A) do RO (A)
SiSi-J: 1 x 3 x 1.5mm² za RAMPU (A)
LiHH: 1 x 2 x 0.50mm² za Printer “paper end”
LiHH: 1 x 4 x 0.50mm² za OPEN/CLOSE/STOP
LiHH: 1 x 2 x 0.50mm² za Boom “Down”
LiHH: 1 x 2 x 0.50mm² za Boom “Up”
LiHH: 1 x 4 x 0.50mm² za FOTO ČELIJU (A)
2 x UTP/SFTP (Rezerva)

- ③ SEMAFOR (A) do RO (A)
SiSi-J: 1 x 3 x 1.00mm²

- ④ CAB. (B) do RO (B)
SiSi-J: 1 x 3 x 1.50mm²
LiHH: 1 x 2 x 0.50mm² za P4
LiHH: 1 x 2 x 0.50mm² za LED MARK. 2
LiHH: 1 x 3 x 0.50mm² za MINI SEMAFOR
LiHH: 1 x 2 x 0.50mm² za LED RASVETA KABINET
LiHH: 1 x 7 x 0.50mm² za RFID Čitač “wiegand”
LiHH: 1 x 7 x 0.50mm² za barcode scanner “wiegand”
LiHH: 1 x 3 x 0.75mm² INTERFON (B) TCS
1 x UTP/SFTP (Rezerva)

- ⑤ RAMPA (B) do RO (B)
SiSi-J: 1 x 3 x 1.5mm²
LiHH: 1 x 2 x 0.50mm² za P5
LiHH: 1 x 4 x 0.50mm² za OPEN/CLOSE/STOP
LiHH: 1 x 2 x 0.50mm² za Boom “Down”
LiHH: 1 x 2 x 0.50mm² za Boom “Up”
LiHH: 1 x 4 x 0.50mm² za FOTO ČELIJU (B)
2 x UTP/SFTP (Rezerva, ELKA RAMPA IDE NA TCP/IP)

- ⑥ SEMAFOR (B) do RO (B)
SiSi-J: 1 x 3 x 1.00mm²

- ⑦ od RO (A) do RO (C)
SiSi-J: 1 x 3 x 1.50mm² (ili 2.50mm²)
LiHH: 1 x 7 x 0.50mm² za RFID Čitač-A “wiegand”
LiHH: 1 x 2 x 0.50mm² za ACC. LOCK A
LiHH: 1 x 4 x 0.50mm² za CC open/close/stop
LiHH: 1 x 2 x 0.75mm² za INTERF. SLUŠALICU (A)
1 x UTP/SFTP za Printer
1 x UTP/SFTP za PLC (A)
1 x UTP/SFTP (Rezerva)

- ⑧ od RO (B) do RO (C)
SiSi-J: 1 x 3 x 1.50mm² (ili 2.50mm²)
LiHH: 1 x 7 x 0.50mm² za RFID Čitač-D “wiegand”
LiHH: 1 x 7 x 0.50mm² za BARCODE -C“wiegand”
LiHH: 1 x 2 x 0.50mm² za ACC. LOCK B
LiHH: 1 x 4 x 0.50mm² za CC open/close/stop
LiHH: 1 x 2 x 0.75mm² za INTERF. SLUŠALICU (B)
1 x UTP/SFTP za PLC (B)
1 x UTP/SFTP (Rezerva)

- ⑨ od RO (C) do NAPLATA
LiHH: 1 x 7 x 0.50mm² za CC
LiHH: 2 x 2 x 0.75mm² za INTERF. SLUŠALICE (A I B)
1 x UTP/SFTP za Printer
1 x UTP/SFTP za SWITCH
2 x UTP/SFTP (Rezerva)

- ⑩ od RO (C) do MONITORINGA
LiHH: 1 x 7 x 0.50mm² za CC
LiHH: 2 x 2 x 0.75mm² za INTERF. SLUŠALICE (A I B)
1 x UTP/SFTP za SWITCH
2 x UTP/SFTP (Rezerva)

- ⑪ RAMPA (A) do FOTO ČELIJE (A)
LiHH: 1 x 4 x 0.50mm²

- ⑫ RAMPA (B) do FOTO ČELIJE (B)
LiHH: 1 x 4 x 0.50mm²

- ⑬ DISPLEJ do RO (C)
SiSi-J: 1 x 3 x 1.50mm²
1 x UTP/SFZP

SEMAFOR STANDARD (230V)

